




**FISA TEHNICA GENERATOR DE CURENT TRIFAZAT  
MODEL: TRS 12000**

<b>GENERATOR DE CURENT TRIFAZAT</b>		<b>MODEL - TRS 12000 - Marca BENZA</b>
<b>Generator</b>		
Tip alternator		SINCRO - Italia
Tensiune	V	400 / 230
Putere generator	KVA (~3 ph)	12,0
Putere generator	KVA (~1 ph)	7.0
Curent maxim pe 400V / 230 V	A	17.34 (~ 3 ph) / 30.40 (~ 1 ph)
Frecvență	Hz	50
Grad de protectie		IP 21
Clasa de izolatie		H
<b>Motor</b>		
Model motor		<b>ROBIN – SUBARU EH 65 DHS</b>
Clasa motor		<b>industrial</b>
Tip motor		Benzina, 2 cilindri, 4 timpi
Racire motor		Cu aer
Putere	CP	22,0
Capacitate cilindrica	cm <sup>3</sup>	653
Turatie nominala	rpm	3000
Sistem de pornire		Start electric
Sistem de aprindere		electronic
Rezervor incorporat	litri	50
Consum min - max (functie de incarcare)	litri/h	2.0 - 4,1
Dimensiuni (LxIxh)	mm	1090 x 800 x 820
Greutate	Kg	161
Nivel de zgomot	dB (A)	82
<b>Dotari standard:</b>		
Cadru metalic acoperit	Da	
Roti de transport (4 buc)	Da - 4 roti	
Maner de ghidare pentru deplasare usoara	Da	
Frana de parcare	Da	
Amortizoare antivibratii	Da - 6 buc	
Acumulator 12 V	In standard	
Amortizoare antivibratii [pentru protectia elementilor din Pb ai bateriei]	Da - 4 buc	
Priza 230 V - speciala (de putere)	Da - 1 buc	
Priza 400 V	Da - 1 buc	
Protectie termica la alternator	Da	
Frecventmetru	Da	
Voltmetru	Da	
Siguranta automata	Da	
Rezervor combustibil cu supapa de unic sens	Da	
Siguranta de protectie diferentiala	Da	

**Garantie:**

- 24 luni de la punere in functiune
- Postgarantie si piese de schimb 10 ani de la livrarea si punerea in functiune.